



3ft

2 odd wire

O

200 AMP

# Simple Requirements for Meter Loop

1. Pole Needs to be at Least 17 ft Long.
2. Pole Needs to be buried 5 ft. deep.
3. Meter can needs to be 6 ft. to top of it from Ground.
4. Circuit box needs to be 6 inches from meter box.
5. Wire needs to be 2 cdd 200 AMP
6. Wire needs to come out of ridge Pipe at Least 36 inches.
7. Two Ground Rods and space 6 ft from each other and No rod to be buried with Pole.
8. Ground Wire Comes out from Meter can box to ground Rods wire not to be spliced.